

Gate
(Top view)



Rotation angle
(z-axis)



Output diagram x–, y–axis



Output diagram z–axis



Description	
Joystick type SK 60–0914	
Number of axes	3–axes, x–axis, y–axis, z–axis
Operation by	Handle with integrated z–axis
Connector: DUBOX Walled Header	8–poles: 76384–308 4–poles: 76384–304
Mating connector: Dubox Housing Anti–rotation locking	8–poles: 65240–08 4–poles: 65240–04
Cross guidance	soft
Center tab	x–, y–axis ±1.75° / z–axis ±3.5°
Switch point α	–
Retaining spring	normal Z–Nr. 60–112

Electrical characteristics	
Resistance value	5 kOhm ± 20%
Power dissipation	0.2 Watt at 40°C per axis
Operating voltage	max. 30V DC

Axes		Potentiometer		Connector side	
	Direction	Colour/ number	Center tab	Joystick in mid–position	
x–axis	+x	21 green			
	Wiper	22 blue	24 grey		
	–x	23 violet			
y–axis	+y	11 yellow			
	Wiper	12 orange	14 brown		
	–y	13 red			
z–axis	+z	53 red			
	Wiper	52 orange	54 brown		
	–z	51 yellow			

Bottom view





					Oberfläche	Maßstab 1:1	Position Menge
				Datum	Name		
				Bearb. 15.01.13	Kiener M.	Joystick	
				Gepr.			
				Norm			
						60-0914	Blatt Bl
Zust.	Änderungen	Datum	Name	Dateiname E:\Dwg\SK 60\...\SK60-0914.dwg			

GENGE &THOMA AG CH-2543 Lengnau/Biel